HHT Basics and Applications

For Speech, Machine Health Monitoring, and Bio-Medical Data Analysis

Norden E. Huang

March 24, 2003

Available Data Analysis Methods for Nonstationary (but Linear) time series

- **Various probability distributions**
- **Spectral analysis and Spectrogram**
- **Wavelet Analysis**
- **Wigner-Ville Distributions**
- **Empirical Orthogonal Functions aka Singular Spectral Analysis**
- **Moving means**
- **Successive differentiations**

Available Data Analysis Methods for Nonlinear (but Stationary and Deterministic) time series

- **Phase space method**
  - **Delay reconstruction and embedding**
  - **Poincaré surface of section**
  - **Self-similarity, attractor geometry & fractals**
- **Nonlinear Prediction**
- **Lyapunov Exponents for stability**

HHT, for Nonstationary, Nonlinear and Stochastic data, consists of the following components:

The Empirical Mode Decomposition:

To generate the adaptive basis, the Intrinsic Mode Functions (IMF), from the data

The Hilbert Spectral Analysis:

To generate a time-frequency-energy representation of the data Based on the IMFs

The Empirical Mode Decomposition Method

Sifting

Empirical Mode Decomposition:

Methodology : Test Data



Empirical Mode Decomposition:

Methodology : data and m1



Empirical Mode Decomposition:

Methodology : data & h1



Empirical Mode Decomposition:

Methodology : h1 & m2



Empirical Mode Decomposition:

Methodology : h4 & m5



Empirical Mode Decomposition

Sifting : to get one IMF component

Two Stoppage Criteria : S and SD

- The S number : S is defined as the consecutive number of siftings, in which the numbers of zero-crossing and extrema are the same for these S siftings.

B. SD is small than a pre-set value, where

Empirical Mode Decomposition:

Methodology : IMF c1



Empirical Mode Decomposition

Sifting : to get all the IMF components

Empirical Mode Decomposition:

Methodology : data & r1



Hilbert Transform : Definition

Comparison between FFT and HHT

Comparisons: Fourier, Hilbert & Wavelet



An Example of Sifting

Length Of Day Data



LOD : IMF


IMF LOD62 : ci(100,8,8; 3a,: 50,3,3;-12,45a, -10)
c1
c2
c3
c4
c5
c6
c7
c8
c9
c10
c11
c12
1965
1970
1975
1980
1985
1990
1995
2000
Time : year

LOD : Data & c12



Length Of Day Data and IMF ci(:, 12)
Deviation from 24 Hr : mil Second
Time : year
4.5
4
3.5
3
2.5
2
1.5
1
0.5
0
-0.5
1960
1965
1970
1975
1980
1985
1990
1995
2000
2005

LOD：Data & Sum c11-12



LOD : Data & sum c10-12



LOD : Data & c9 - 12



LOD : Data & c8 - 12



LOD：Detailed Data and Sum c8-c12



LOD : Data & c7 - 12



LOD：Detail Data and Sum IMF c7-c12



LOD：Difference Data – sum all IMFs



Traditional View

a la Hahn (1995) : Hilbert



LOD：Mean envelop from 11 different siftings



Mean Envelopes for Annual Cycle IMFs



Comparisons

	Fourier	Wavelet	Hilbert
Basis	a priori	a priori	Adaptive
Frequency	Convolution: Global	Convolution: Regional	Differentiation: Local
Presentation	Energy-frequency	Energy-time-frequency	Energy-time-frequency
Nonlinear	no	no	yes
Non-stationary	no	yes	yes
Feature extraction	no	discrete : no continuous: yes	yes

Characteristics of Data from Nonlinear Processes

Duffing Pendulum



$$\frac{d^2x}{dt^2} + x + \varepsilon x^3 = a \cos \gamma t$$

$$\frac{d^2x}{dt^2} + x(1 + \varepsilon x^2) = a \cos \gamma t$$

Hilbert's View on Nonlinear Data

Duffing Type Wave

Data: $x = cos(wt+0.3\ sin2wt)$



Duffing Type Wave

Perturbation Expansion

Duffing Type Wave

Wavelet Spectrum



Duffing Type Wave

Hilbert Spectrum



Duffing Type Wave

Marginal Spectra



Technology Description

Results:

- **An adaptive basis to filter signal**
- **Frequency defined as a function of time by differentiation rather than convolution analysis**
- **Sharp identification of embedded structures**
- **A more simple and revealing interpretation than prior methods**

Market Potential

Key Considerations

- Conceptually simple and direct
- An efficient, adaptive, user-friendly set of algorithms
- Capable of analyzing nonlinear and nonstationary signals
- Improves accuracy by using an adaptive basis to preserve intrinsic properties of data
- Yields results with more physical meaning and a different perspective than existing tools
- Useful in analyzing a variety of from nonlinear and nonstationary processes

Possible Applications

- **Vibration, speech and acoustic signal analyses : this also applies to machine health monitoring.**
- **Non-destructive test and structural Health monitoring**
- **Earthquake Engineering**
- **As a nonlinear Filter**
- **Bio-medical applications**
- **Time-Frequency-Energy distribution for general nonlinear and nonstationary data analysis, for example, turbulence**

Sound Enhancement :

- Fourier filter is linear and stationary; it works in Frequency domain
- Fourier filter will take away harmonics and dull the sharp corners of all the fundamentals
- EMD filter is nonlinear and intermittent; it works in Time domain
- EMD filter will take the unwanted noise of short periods and leaves the fundamentals unchanged

EMD as Filter

An Example :
Removal of Unwanted Sound

HHT Filtering to Separate
Ding from Hello

Data : Hallo + Ding



IMF : Hallo + Ding



Filter for Hallo + Ding is defined as

- c1(15200:30000) = 0;
- c2(15200:30000) = 0;
- c3(15200:21400) = 0;
- For c4 to c9 : $q=[\cos(2\pi\ t/1200) +1]/2$;

  for t=0:1200, centered at 15200.

IMF Filtered : Hallo



Data and Filtered Components



Hilbert Spectrum : Hallo + Ding



Hilbert Spectrum Filtered : Hallo



Sound Effects : Data



Raw data : Hallo + Ding


Sound Effects : Fourier Filtered
Fourier 3K
Fourier 2K
Original
Fourier 1K

Sound Effects : EMD Filtered

EMD Filtered Hello

EMD Filtered Ding

Original Sound

Hilbert Spectra for Different Speakers

Potential Application for Speaker Identification

Difference between Speakers





IMF : Hello N



IMF : Hello N
0
30000
60000
90000
120000
150000
180000
210000
240000
270000
300000
330000
0
0.5
1
1.5
2
2.5
3
Time : second
x 10^4

IMF : Hello J


IMF : Hello J
0
30000
60000
90000
120000
150000
180000
210000
240000
270000
300000
330000
0
0.5
1
1.5
2
2.5
3
Time : second
x 10^4

Hilbert Spectrum : Hello N



Hilbert Spectrum : Hello J




Narrowband Spectrogram : Hallo 1024
Frequency : Hz
Time : second


Wideband Spectrogram : Hallo 64
Frequency : Hz
Time : second


Wavelet Spectrum : Hello 5:2048
Frequency : Hz
Time : second


Hilbert Spectrum : Hello
Frequency : Hz
Time : second

Detailed Hilbert Spectrum : Hello N



Detailed Hilbert Spectrum : Hello J



Detailed Wavelet Spectrum : Hello N



Detailed Wavelet Spectrum : Hello J



100 Smoothed H Spectrum : Hello N



200 Smoothed H Spectrum : Hello N



EMD as Filters :

The Effects of Harmonics

Speech Analysis :

Hello : The Effects of Harmonics and EMD filtering



Speech Analysis :

Hello : Details of the Difference Data



Speech Analysis :

Hello : The Hilbert Transform of the Difference Data



Speech Analysis :

Hello : The Effects of Harmonics and EMD filtering



Summary

- **Numerous application possibilities**
- **Intellectual property protected**
- **Concepts demonstrated in many applications**
- **Licensing and partnering opportunity**
- **Enabling technology with significant commercial potential**
- **Significant benefits**
  - Precision, flexibility, accuracy, easy implementation,

Contact Info

For more information, please contact:

Evette Brown-Conwell

- **Phone: (301) 286-0561**
- **E-mail: evette.r.conwell@nasa.gov**